

CH1-7144



| | |
|-----------------------------------|--|
| Radio Model | Motorola GP900/1200, HT1000, HTS2000, MTX8000/9000 |
| Battery Model | AM7143, AM7143N, AMN7143N-18, AM7144, AM7144-17, AM7144N, AM7144N-27, NTN7143, NTN7144 |
| Mechanical Characteristics | |
| Dimension | 132.1 X 113.8 X 67.8 mm |
| Weight | Approx. 230g - <i>without PSU</i> Approx. 800g - <i>with PSU</i> |
| Plastic Material | ABS+PC |
| Charge Status Display | Dual LED display |
| Electrical Characteristics | |
| Chemistry Supported | Ni-Cd, Ni-MH |
| Input voltage | 12V |
| Max. Charge Current | 1000mA |
| Power supply | External with safety approval |
| AC Input | 110V, 230V, and 240V |
| Charge Time | 1 ~ 3 hours depend on battery type |
| Charge Mode | Ni-Cd / Ni-MH: Constant current |
| Temperature | -5 ~ +40°C (+23 ~ +104°F) |
| Agency approval | CE for the charging unit |